

THE NEXT GENERATION OF ELECTRONIC BALLASTS... IS HERE

# NEXTGEN™

ELECTRONIC BALLAST

600W  
90V-260V



## FEATURES

- 90v-260v Input Voltage
- Runs H.P.S. Bulbs
- 30% more Light than a Core and Coil Ballast
- Fast Lamp Ignition
  - Cold Lamp Starts in Less than 2 Seconds
  - Hot Lamp Restart in Less than 2 Minutes
- Universal Lamp Receptacle
- Bulb can be ran up to 65' from Ballast
- Flicker-Free Operation
- Constant Lamp Voltage Prolongs Bulb Life

## SPECIFICATIONS

5.7 amps at 120v

2.8 amps at 240v

Power Factor: 99.99

Max Lamp Cord Length: 65'

Dimensions: 9.5" x 7" x 2"

Weight: 4.25 lbs

Operating Temp: 0-140°F

Cold Lamp Start: < 2 sec.


Hot Lamp Start: < 2 min.

## INSTRUCTIONS

1. Hang your reflector in the appropriate location and screw your lamp into the reflector socket.
2. Plug in the reflector lamp cord into the appropriate receptacle on the ballast. You cannot run 2 bulbs at the same time.



3. Attach the power cord to the power receptacle on the ballast.
4. Plug power cord into your power source (wall outlet or Lighting Controller).



1. C.A.P. & Common
2. HF
3. PL
4. Foreign

## WARRANTY

5 Year  
Warranty\*

\*Certain conditions apply

C.A.P. warrants the NextGen Digital Ballast to be free from defects in materials or workmanship for a period of 5 years. 3 Year full warranty and 2 year pro-rated warranty. Misuse, abuse, or failure to follow instructions are not covered. C.A.P. will, at our discretion, repair or replace the product covered under this limited warranty that are returned to our facility. To request warranty service, you must take the product to the place of purchase. If warranty service is required, C.A.P. will issue a RMA number. The product must be shipped back to C.A.P. in the original or equivalent packaging, prepaid shipping charges, and insured. We can not cover shipping damages. Pack your product well.



**CUSTOM AUTOMATED PRODUCTS**

4745 Hiers Ave., Suite A, Riverside, CA 92505

www.capcontrollers.com • 866-476-9768